

Meter Socket Adapters Prohibited Installations

LPEA reserves the right to deny the use of an MSA for any purpose and at any point during the interconnection process. This is a non-exclusive list of prohibited installations to aid members and their installers in determining whether a MSA will be allowed. However, LPEA may determine at its sole discretion that an MSA is not allowed in a particular instance even if that is not documented on this list of prohibited installations.

- 1) Any meter socket other than a 2S 240V 200A
- 2) Any metering configuration with CTs and/or PTs
- 3) Meter sockets that are not securely attached to the building
- 4) Ganged meter sockets where the conduit and socket adapter would impede on adjacent sockets. This includes double meter pedestals.
- 5) Meter sockets that already have another meter socket adapter (aka 'meter collar' like a surge protector)
- 6) If a member has a pigtail meter for controlling an ETS. **The member could replace the pigtail meter with a PLC Connect or time clock to control the ETS and then a MSA could be used.*
- 7) Any location where a Shark fin collector is installed behind a meter